

# **Electronic Pressure Switch**

# **EDS 8000**

(Menu navigation according to VDMA)

## **User Manual**

(Translation of original instructions)



# **Table of Contents**

1	SAFETY INFORMATION	.3
2	FUNCTIONS OF THE EDS 8000	.3
3	INSTALLATION	.3
4	CONTROLS OF THE EDS 8000	.4
5	DIGITAL DISPLAY	.4
6	OUTPUT FUNCTION	7
6.1.1	Switching Outputs	.7
6.2	Setting ranges for the switching outputs	.8
7	MENU NAVIGATION	.9
7.1	Main menu	9
7.2	Extended functions	10
8	ERROR MESSAGE	11
9	PIN ASSIGNMENT	11
10	TECHNICAL SPECIFICATIONS	12
11	ORDERING DETAILS	13
12	ACCESSORIES	14
12.1	For electrical connection	14
12.2	For mechanical connection	14
13	INSTRUMENT DIMENSIONS	15

## 1 Safety Information

Before commissioning,

- check the instrument and any accessories supplied
- read the operating instructions
- ensure that the instrument is suitable for your application.

If the instrument is not handled correctly, or if the operating instructions and specifications are not adhered to, damage to property or personal injury can result.

#### 2 Functions of the EDS 8000

Depending on which model you have, the instrument offers the following functions:

- Display of the actual pressure in **psi**, **Mpa or bar**
- Switching of the switch outputs in accordance with the pressure and the pre-set switching parameters
- Menu navigation in accordance with the VDMA standard 24574-1
- Coloured LED backlight indicates the switching status

#### 3 Installation

The EDS 8000 can be mounted directly via the pressure connection or indirectly on a hydraulic block using a hose or a minimess line (for torque value, see Chapter 9 - Technical specifications).

For optimum alignment, we recommend connecting the EDS 8000 mechanically using a rotating adapter (for Mechanical Accessories see Chapter 12.2).

The electrical connection must be carried out by a qualified electrician according to the relevant regulations of the country concerned (VDE 0100 in Germany). The housing of the pressure switch must be properly earthed. When fitting into a hydraulic block, it is sufficient if the block is earthed via the hydraulic system. When installing with a minimess hose, the housing must be earthed separately (e.g. with a screened cable).




#### **CAUTION:**

The EDS 8000 must be fitted using a suitable open-end wrench (across flats 27) on the hexagon nut of the pressure connection. Do not install the EDS 8000 by gripping the housing, as this would damage the housing or the entire instrument.

Additional installation suggestions which, from experience, reduce the effect of electromagnetic interference:

- Make line connections as short as possible
- Use screened cabling (e.g. LIYCY 4 x 0.5 mm<sup>2</sup>)
- The cable screening must be fitted by qualified personnel subject to the ambient conditions and with the aim of suppressing interference
- Keep the unit well away from the electrical supply lines of power equipment, as well as from any electrical or electronic equipment causing interference

#### 4 Controls of the EDS 8000



Use the keys to select the next menu point, or alternatively to adjust the values.



- To scroll through the menu
- (E)
- To select the menu point

To confirm value

- To increase the value
- Hold the key down to fast-scroll through the parameter values

# 3 1 2


## 5 Digital display

Once the power supply has been switched on, the device briefly flashes "**EdS**", and then begins to show the actual pressure.



To check the unit of measurement being used for the pressure indication, press the right-hand key. Depending on the setting, bar, psi or MPa will be shown.

The backlight changes colour according to the settings of the switch outputs and their switch points, i.e. when the switch output is inactive or low-level, the relevant backlight is "green", when the switch output is active or high-level, the relevant backlight is "red".



# Reading the digital display

Description	Representation on 7-segment display	ASCII representation		
Switch point, output 1	5P I	SP1		
Switch-back point, output 1	rP I	RP1		
Switch point, output 2	5P2	SP2		
Switch-back point, output 2	rP2	RP2		
Pressure window upper value, output 1	FH I	FH1		
Pressure window lower value, output 1	FL I	FL1		
Pressure window upper value, output 2	FH2	FH2		
Pressure window lower value, output 2	FL2	FL2		
Extended functions	EF	EF		
Reset	rE5	RES		
Switch delay time, output 1	d5 l	dS1		
Switch delay time, output 2	d52	dS2		
Switch-back delay time, output 1	dr l	dR1		
Switch-back delay time, output 2	dr2	dR2		
Output 1	ou !	Ou1		
Output 2	002	Ou2		
Normally open when hysteresis function is active	Hno	HNO		
Normally open when window function is active	Fno	FNO		
Normally closed when hysteresis function is active	Hnc	HNC		
Normally closed when window function is active	Fnc	FNC		
Unit conversion	Un ₁	Uni		
Units in bar	ЬRr	Bar		
Units in MPa	NPR	MPa		
Units in psi	P5 ,	psi		
Maximum value	H I	HI		
Error indication	Err	ERR		
Delete				
Extended functions	EF	EF		
Yes	YE5	Yes		
No	no	No		
Version	üЕr	Ver		



## NOTE:

- If the actual pressure exceeds the instrument's nominal pressure it can no longer be displayed. The nominal pressure flashes in the display. As a result, when the menu point Max Value (Hi) is selected, the value of the highest measured pressure which has been stored flashes until the instrument is reset (rES).
- If the actual pressure is less than 0.6 % of the nominal range, 0 bar is displayed.

## 6 Output function


#### 6.1 Switching Outputs

The EDS 8000 has 2 switching outputs. The following settings can be made under the basic settings:

## 6.1.1 Switch point setting (SP)

One switch point and one switch-back point can be set for each switching output. The particular output will switch when the set switch point is reached and switch back when the pressure drops below the switch-back point.

Example for switch point 1 (normally closed and normally open function):



Abbreviations:

"SP1", "SP2" = switch point 1 / switch point 2

"RP1", "RP2" = switch-back point 1 / switch-back point 2

"HNO", = normally open when hysteresis function is active "HNC" = normally closed when hysteresis function is active



#### NOTE:

 It is only possible to set the switch point (SP) if it is higher than the respective switch-back point (RP). In the case of low SPs we recommend setting the RP first.


#### 6.1.2 Window function setting (Fno / Fnc)

The window function allows you to monitor a range. An upper and a lower switch value can be entered for each switch output. These values determine the range.

The relevant output will then switch when the pressure enters this range.

When the pressure leaves this range, i.e. when the switch-back point has been reached, the output switches back. The lower switch-back value is just below the lower switch value. The upper switch-back value is just above the upper switch value. The range between the switch value and the switch-back value forms a safety margin which prevents unwanted switching operations from being triggered (such as those triggered by the pulsations of a pump).

Example for switch output 1 (normally closed and normally open function):



<u>Abbreviations:</u> "FH1", "FH2" = upper switch value 1 / upper switch value 2

"FL1", "FL2" = lower switch value 1 / lower switch value 2

"FNO" = normally open when window function is active

"FNC" = normally closed when window function is active



#### NOTE:

- It is only possible to set the switch point (SP) if it is higher than the respective switch-back point (RP). In the case of low SPs we recommend setting the RP first.
- The window function only works properly (switching on and off) if all switch values (including the safety margin) are above 0 bar and below the nominal pressure range.

#### 6.2 Setting ranges for the switching outputs

Measuring range		Lower I		Upper lir	nit of SP	Min. diffe		Increm	ent
			_			RP and	SP or		
						FL and F	-H		
in psi	in bar	in psi	in bar	in psi	in bar	in psi	in bar	in psi	in bar
0 500	0 25	5	0,25	500	25	5	0,25	1	0,05
01000	0 40	10	0,40	1000	40	10	0,40	2	0,10
03000	0100	30	1,00	3000	100	30	1,00	5	0,20
06000	0250	60	2,50	6000	250	60	2,50	10	0,50
09000	0400	90	4,00	9000	400	90	4,00	20	1,00
	0600		6,00		600		6,00		1,00

<sup>\*</sup> All ranges given in the table can be adjusted by the increments shown.

## 7 Menu navigation


The EDS 8000 can be adapted to suit the particular application as required by changing multiple settings. These settings are combined in a single menu.




#### NOTE:

- If no key is pressed for approx. 60 seconds, the menu closes automatically, and any changes that may have been made will not be saved.
- If both keys are pressed at the same time, the menu closes automatically and any changes made are saved.
- When an adjusted parameter is confirmed, the set value is displayed for a second before returning to the relevant menu point.

#### 7.1 Main menu



## 7.2 Extended functions



### 8 Error message

If an error is detected, a corresponding error message appears that must be acknowledged by pressing any key.

Possible error messages:

**E.10** A data error was detected in the saved settings. This could be due to strong electromagnetic interference or a component fault.

Action: Press and confirm "RES" by pressing "Yes". The factory settings will be restored for all adjustable parameters and all minimum and maximum values will be deleted. Enter the data again from the beginning.

**E.12** An error was detected in the saved calibration data. This could be due to strong electromagnetic interference or a component fault.

**Action**: Disconnect then reconnect the supply voltage to the instrument. If the error persists, the instrument must be returned to the factory for recalibration or repair.


**E.21** A communication error was detected within the instrument. This could be due to strong electromagnetic interference or a component fault.

**Solution**: Press E. If the error persists, disconnect then reconnect the supply voltage to the instrument. If the error still persists, please contact our service department.

## 9 Pin assignment

Version with 2 switch outputs:

Male 4 pole, M12x1




## 10 Technical specifications

Input data					
Measuring ranges	500; 1000; 3000; 6000; 9000 psi				
5 5	25; 40; 100; 250; 400; 600 bar				
Overload pressures	1160; 2900; 7250; 11600; 14500 psi				
·	80; 80; 200; 500; 800; 1000 bar				
Burst pressure	2900; 7250; 14500; 29000; 29000 psi				
	200; 200; 500; 1000; 2000; 2000 bar				
Mechanical connection	SAE 6 9/16-18UNF2A; G1/4 A DIN 3852, Form E				
Torque value	15 lb-ft (20 Nm)				
Parts in contact with fluid:	Mechanical connection: stainless steel				
	Sensor cell: stainless steel				
	Seal: FPM				
Output data					
Accuracy to DIN 16086,	≤ ± 0.5 % FS typ.				
Max. setting (Display)	≤ ± 1 % FS max.				
Repeatability	≤ ± 0.5 % FS max.				
Temperature drift	≤ ± 0.017 % FS / °F [0.03 % / °C] max. zero point				
	≤ ± 0.017 % FS / °F [0.03 % / °C] max. range				
Long-term stability	≤ ± 0.25 % FS / year max.				
Switch outputs					
Туре	2 PNP transistor outputs				
Switching current	max. 250 mA per switching output				
Switching cycles	> 100 million				
Reaction time	< 10 ms				
<b>Ambient Conditions</b>					
Compensated temperature range	-13 +185 °F [-25 + 85 °C]				
Operating temperature range *	-13 +212 °F [-25 + 100 °C]				
Storage temperature range	-40 +185 °F [-40 + 85 °C]				
Fluid temperature range *	-13 +257 °F [-25 + 125 °C]				
Nominal temperature range of display	+5 +185 °F [-15 + 70 °C]				
(read-out)					
C € mark	EN 61000-6-1 / 2 / 3 / 4				
Vibration resistance to	approx. 10 g				
DIN EN 60068-2-6 at 0 500 Hz					
Shock resistance to	approx. 50 g				
DIN EN 60068-2-29 (11 ms)					
Protection class to DIN 40050	IP 67 (when an IP 67 connector is used)				
Other data					
Supply voltage	9.6 32 V DC				
Current consumption	max. 35 mA				
	(inactive switch output)				
Display:	4-digit, LED, 7-segment,				
	Height of digits 4.5 mm				
Life expectancy	> 10 million cycles (0 100 %)				
Weight:	approx. 70 g				
Life expectancy Weight:	> 10 million cycles (0 100 %)				

**FS** (Full Scale) = relative to the complete measuring range

<sup>\*</sup> extended temperature range possible. By separate request.

## 11 Ordering details



400 = Standard in psi

000 = Standard in bar


#### 12 Accessories

#### 12.1 For electrical connection

## **ZBE 06 (4 pole)**

Female connector, right-angle Part No.: 6006788






#### **ZBE 06-02 (4 pole)**

Female connector, right-angle with 2m cable.

Part No.: 6006790





## **ZBE 06-05 (4 pole)**

Female connector, right-angle with 5m cable

Part No.: 6006789

Colour code: Pin 1: brown

Pin 2: white Pin 3: blue Pin 4: black


#### 12.2 For mechanical connection

#### **ZBM 14**


Adapter female thread G1/4 - male thread G1/4 (rotating)

Part No.: 907818





## 13 Instrument dimensions



#### **HYDAC ELECTRONIC GMBH**

Hauptstr.27 D-66128 Saarbrücken Germany

Web: E-Mail:

Tel.: +49 (0)6897 509-01 Fax.: +49 (0)6897 509-1726

#### **HYDAC Service**

For enquiries about repairs or alterations, please contact HYDAC Service.

#### **HYDAC SERVICE GMBH**

Hauptstr.27 D-66128 Saarbrücken Germany

Tel.: +49 (0)6897 509-1936 Fax.: +49 (0)6897 509-1933

#### Note

The information in this manual relates to the operating conditions and applications described. For applications and operating conditions not described, please contact the relevant technical department.

If you have any questions, suggestions, or encounter any problems of a technical nature, please contact your Hydac representative.

Subject to technical modifications.